# PRESERVATION COPY BY N2CKH

# FL-110 LINEAR AMPLIFIER



### GENERAL

The FL-110 is an all solid state linear amplifier designed to match the FT-301S and FT-7 transceivers covering ham bands 160 through 10 meters.

The FL-110 uses a pair of SRF-1427 transistors in a push-pull, broad-band linear amplifier circuit configuration with negative feedback reducing the distortion and spurious radiation.

The Automatic Level Control Circuit controls the exciter gain to allow the highest average power without distortion caused by peak clipping, and, protects the PA transistor from destruction due to overdrive.

An internal change-over relay is operated automatically by either a transmitted signal or PTT switch in the exciter.

### CAUTION

DO NOT EXCEED RATED DRIVE POWER OR DESTRUCTION OF THE PA TRANSISTOR MAY RESULT. PRESERVATION COPY BY NZCKH

# SPECIFICATIONS

Frequency Coverage - Ham bands 160 through 10 meters.

Wave Form - SSB, AM, CW and FSK

Max. Drive Power - 15 watts CW, SSB
4 watts AM, FSK

Input Impedance - 50 ohms unbalanced

Output Impedance - 50 ohms unbalanced

Circuit

Max. Input Power - 200 watts DC SSE, CW 75 watts DC FSK 50 watts DC AM

Distortion - Better than 31 db

Spurious Radiation - Less than -40 db

Power Requirement - 13.5V DC +10% negative ground Receive 0.05 amps

Transmit 17 amps at 100 watts

Output 14 MHz

Transistorized push-pull, wide-band linear amplifier.

Size - 120(W) x 100(H) x 200(D) m/m

Weight - 2.5 kg

# SEMICONDUCTOR COMPLEMENT


IC	"PC271G	(1)	DIODE	15-1007	(12)
TR	2SC372Y 2SC735Y 2SD235 SRF1427	(1) (1) (1) (2)		10D1 10D10 SG103D SR103D CW01B	(3) (2) (1) (2) (1)

# "CAUTION"

EXCEEDING CURRENT LEVEL AS LISTED IN OPERATING MANUAL MAY CAUSE SPURIOUS IN VIOLATION OF FCC RULE 97.73.

Digitized by the Internet Archive in 2023 with funding from Amateur Radio Digital Communications, Grant 151

# CONTROLS, INDICATORS & CONNECTORS



(8)


(9)

(10) PTT

(11) GND

ANT

POWER



# Front Panel

(1)	POWER	-	Switch to turn power "ON".
(2)	DELAY		Switch selects relay hold time for carrier operated change-over. Relay time is 0.1 - 0.2 seconds for FAST and 0.3 - 1.0 seconds for SLOW positions.
(3)	BAND	1.	Switch selects the Amateur band between 160 and 10 meters.
	INDICATORS		
(4) (5) (6)	REC: OPER: AFP:		Green lamp indicates receive mode. Red lamp indicates transmit mode. Red lamp indicates that the AFP circuit is in operation and that the linear amp is shut down.
		Rear Panel	
(7)	INPUT	-	Input connector for the drive from exciter.

Antenna connector.

Ground connection.

is included.

DC-13.5V, Z0A power input. External PTT control terminal

Switch to select relay polarity.

COLUMN DESCRIPTION OF STREET





Server to action college or every

Capital promotion.

TTS BULL

mate (III)

### INSTALLATION AND OPERATION

The FL-110 Linear Amplifier is installed and operated very simply. It requires only a 13.5 volts DC power source and an antenna. However, the following points are very important, therefore, please read them carefully before installing and operating the FL-110.

# CAUTION

PERMANENT DAMAGE WILL RESULT IF THE WRONG POLARITY OF DC POWER VOLTAGE IS APPLIED TO THE FL-110. OUR WARRANTY DOES NOT COVER THE DAMAGE WHICH WOULD RESULT TO THE AMPLIFIER IF THE INCORRECT POLARITY WAS APPLIED.

The FL-110 will operate satisfactorily from any 12 - 14 volts DC power source having a 20A current capacity. When making connections to the power source, be certain the the ORANGE lead is connected to the positive (+) and the BLACK lead to the negative (-).

The power cable should be as short as possible to minimize voltage drop and to provide a low impedance path from the FL-110 to the power supply.

Prior to operating the FL-110 in a mobile installation, the automobile's voltage regulator setting should be checked. In many vehicles, the voltage regulator is very poor and, in some cases, the regulator may be adjusted for an excessively high charging voltage. It is necessary to carefully set the regulator so that the highest charging voltage does not exceed 14 volts.

No special installing precautions need be observed if adequate ventilation space is available. However, it is recommended that excessively warm locations, such as car heater ducts, should be avoided. The FL-110 should be installed in such a way so that the heat sink is on top.

It is also very important that the antenna used with the FL-110 presents a fairly close 50 ohms non-reactive load. If the SWR is as high as 2:1, the output power decreases and the AFP circuit will work with SWR 3:1 to protect the power transistor.

STORY AND SHARING ALL DATEST

avigate may fattenge from Latterer at indifferent small filled a set of the description o

# HOLTBER

PRINCIPLE TO THE PARKAGE WHILL HOULD BE SOLVED B

The PL-110 will appears acquired promote promote the old of old the party of the old of the party of the part

The power calmy simulates as story as passellle to microrite valle properties and you provide the properties of the time of the properties of the properties

regimes requisions resting about the country of the restallation, the successful to copie or regulator resting about the charges, the many vertical to access regulator to access and, he comes country, the requisions one an expensively their charging voltages, it is consensury to adjust the injured to the regulator of the regula

on the special resulting granulations and be observed of adoption and the special states are special states and the special states and the special states are special states are special states are special states and the special states are s

The FL-110 can be keyed either manually or automatically.

For manual operation, use the accessory relay output of the transceiver in use as illustrated in Fig. 1. With this interconnection, the FL-110 is keyed by push-to-talk operation of the transceiver.

Carefully examine the relay function of the transceiver.

The switch marked PTT on the rear panel should be set to (-) for the transceiver which has the accessory relay contact close to ground in transmit (FT-101 series). It should be set to (+) position for the transceiver which has the relay contact close to a positive voltage in transmit (FT-301 series).

Use a coax cable for the connection between the transceiver and the FL-110 linear amplifier.

# CAUTION

THE DRIVING POWER SHOULD NOT EXCEED 15 WATTS UNDER ANY CIRCUMSTANCES.

DO NOT KEY THE FL-110 WITHOUT THE PROPER ANTENNA BEING CONNECTED.

THE COLLECTOR OF THE PA TRANSISTOR IS CONNECTED TO THE POWER SOURCE AND DRAWS 5 MILLIAMPS WHEN THE POWER SWITCH IS AT "OFF" POSITION. THEREFORE, IT IS RECOMMENDED TO DISCONNECT POWER CABLE FROM THE BATTERY WHEN THE FL-110 IS NOT BEING USED FOR SEVERAL MONTHS.




Figure 1

Figure 2

a place of the parties are placed and the parties for the party and the parties are

The state of the second of the

Carefully somethy on relay conduct of the transcenter.

bandan at another factors of the sate billions which are the sate of the sate

the name of the first and the summerful between the friends will also and the first an

# POSTNAR

STYLE OF CHARLE TOR BUILDING STREET THE PERSON

AND AFTER PERSONAL PROPERTY OF THE PERSONAL PR

THE COURSE OF THE PARTY STATE OF



5 Subgiv

I stonil

When the power switch is set to "OFF" position, the FL-110 does not operate and the antenna is directly connected to the transceiver. When the power switch is "ON", a green lamp lights up and the FL-110 is keyed together with the transceiver. On transmit, a red lamp lights up.


The FL-110 can operate automatically when the transceiver is operated by VOX (voice controlled) mode. The transmitter carrier from the transceiver controls the change-over relay in the FL-110. The relay hold time is set to either FAST or SLOW to select delay time of the change-over relay. When the FL-110 is operated with the lower driving power of less than I watt, the carrier operated change-over circuit does not function.

# GAUTION

IF THE AFP (AUTOMATIC FINAL PROTECTION) CIRCUIT STARTS TO WORK, A RED WARNING LAMP LIGHTS UP SHOWING THAT THE LINEAR AMPLIFIER IS NOT FUNCTIONING.

IF THIS HAPPENS, TORN THE POWER SWITCH "OFF" AND CHECK FOR THE CAUSE OF TROUBLE WITCH WILL BE FITHER A DEFECTIVE ANTENNA SYSTEM OR OVERDRIVE FROM THE EXCITER.

AFTER ELIMINATING THE PROBLEM, THE AFP CIRCUIT CAN BE RESET BY TURNING THE POWER SWITCH "ON".



### CIRCUIT DESCRIPTION

The FL-110 consists of four major parts -- COUPLING UNIT, CONTROL UNIT, BOOSTER UNIT and LPF unit. On receive mode, a received signal is fed through J1, RL1 and J2 to the transceiver astenna terminal.

On transmit; the output signal from the transceiver antenna passes through the CM coupler T161 in the coupler unit PB-1680 where the RF voltage is detected and applied to the control unit PB-1681 in order to activate the relay RL1.

A forwarding wave is detected by the voltage doubler rectifier D101 and D103, 1S-1007 and a reflected wave is detected by D102 and D104, 1S-1007. The rectified DC voltages are applied to a comparator Q204, aPC-271C which controls relay driver, Q201, ZSC372Y and Q202, ZSC735Y. With high reflected wave, such as VSWR 1:3, the output of Q204 is low and the relay driver circuit does not function.

A part of the DC voltage obtained from the forwarding wave is applied to the AFP circuit in order to operate RL201 to disconnect the activating voltage for RL1 thus protecting the PA transistors from damage due to overdrive. The relay hold time is set to either FAST or SLOW by adding C201 for a longer discharge time.

When RL1 is activated, the bias voltage is applied to the PA transistors and the amplifier starts to operate.

The driving power is fed through the equalizer circuit consisting of R1216, R1211, C1201, C1202, R1201, R1202 and L1201 to the input transformer T1201 to be amplified by Q1201 and Q1202, SRF-1427 which works as a wide-band linear amplifier in a push-pull configuration.

The Negative Feedback circuit consisting of Ri206, Li204, Ri204 and Li203 improves the stability and the linearity of the PA stage.


The 13.5 Volt DC voltage is regulated to 0.65 volts by a regulator Q1203, 25D235 to be used as bias for Q1201 and Q1202. Q1203 is controlled by the voltage generated by D1201 and D1202, 10D10 which varies in accordance with the temperature of the final transistor in order to protect the final transistor.

The amplified output is fed through the Low-Pass Filter Unit, PB-1577 which reduces the harmonic radiation, and then passes through relay RL1 to the antenna.

A portion of the output power is compled through T301 to the AFP circuit.

The DC voltage obtained by rectifying the forwarding power with D302 and D304, 18-1007 is fed to Q203, CW018 which controls RL201 to open RL1 when the output power exceeds preset value set by VR301.

The DC voltage obtained by a reflected power caused by high VSWR (more than 1:3) also controls Q203 to open RL1.




### MAINTENANCE AND ALIGNMENT

Your FL-110 Linear Amplifier has been carefully aligned and tested at our factory prior to shipment. The reliability of the solid state devices used in the FL-110 should provide years of trouble-free service if the amplifier is not abused, and, normal routine maintenance is carried out.

The following precautions should be observed to prevent damage to the FL-110.

- (a) Do not exceed 14 Volts DC at the power receptacle. When operating mobile, check the battery voltage under load (full output on CW) with the engine running fast enough so that the car ammeter shows a "charge". Also, do not operate the FL-110 if the supply voltage is below 12 Volts DC.
- (b) Avoid direct exposure to sunshine or water.
- (6) Avoid extremely warm locations and maintain free air circulation around the heat sink.

The FL-110 does not require realignment with normal usage. Service, or replacement of a major component, may require subsequent realignment.



BOTTOM VIEW



#### REALIGNMENT PROCEDURE

### (1) DELAY ADJUSTMENT (VRZ01)

The relay hold time can be adjusted by VR201. Clockwise rotation of VR201 will produce longer hold time.

### (2) BALANCE ADJUSTMENT OF CM COUPLER (TC101, TC301)


Set the power switch to "OFF". Connect during load/wattmeter, YP-150, to antenna connector. Set the output power of the exciter to 10 watts on the 3.5 MHz band. Connect a VTVM between a check point marked "R" in the control unit (+) and ground (-). Adjust TC101 for a minimum VTVM reading (less than 0.05V).

Connect plus (+) lead of VTVM to TP301 in the LPF unit. Set the power switch to "ON". Adjust TC301 for a minimum VTVM reading (less than 0.1 volts).

# (3) AFP CIRCUIT ADJUSTMENT (VRZ02, VRZ03, VR301)

Prior to this adjustment, complete the adjustment of CM coupler described in Step (2).

Set VR202 to a fully clockwise position and VR203 to a fully counter-clockwise position in the control unit. Set VR301 in the LPF unit to a fully clockwise position. Connect the dummy load/wattmeter to the antenna connector and apply 3.5 MHz 20 watts carrier signal from the exciter. Slowly advance VR202 in a counter-clockwise direction and set VR202 to the point where the AFP relay is activated. Turn the power switch "OFF" and adjust the exciter output to 15 watts. Turn the power switch "ON". The AFP circuit should not work with a 15 watts drive power. If it should work with 15 watts, slowly advance VR203 in a clockwise direction.



RICHT SIDE VIEW



Repeat this procedure until the AFP circuit works without fail with a 20 watts input and does not work with a 15 watts input.

Then, rotate VR301 in a counter-clockwise direction until the AFP circuit is activated. Slowly rotate the VR301 back approximately 5 degrees in a clockwise direction. Set the exciter to receive. Connect VSWR meter, antenna coupler and dummy load/wattmeter to the antenna connector. Transmit on 3.5 MHz and adjust exciter output and antenna coupler to produce VSWR 1.3 at 70 watts output. Slowly rotate VR203 in a clockwise direction until the AFP circuit is activated.


# (4) CARRIER CONTROL GIRCUIT ADJUSTMENT (VR101)

After completion of above procedure, disconnect the PTT connection between the exciter and FL-110. Set VR101 to a fully clockwise position. Turn the power switch "ON" and apply 3.5 MHz 10 watts CW signal from the exciter. Garefully rotate VR101 in a counter-clockwise direction until the relay is activated. Recover the PTT connection.

# (5) PA BIAS ADJUSTMENT (VR1201)

This adjustment is only required when the PA power transistors are replaced. Otherwise, please do not adjust the VR1201 as an incorrect setting will result in damage to the PA transistors.

Connect 1A ammeter in the power supply line (cut red wire) to measure PA collector idle current. Disconnect the exciter from the FL-110. Set PTT switch to (-) position. Connect PTT terminal (pin 4) to ground. Turn the power switch "ON". Adjust VR1261 for 100mA idle current. Remove the ammeter from the circuit and recover the wiring cut for the ammeter installation.




LEFT SIDE VIEW













LPR UNIT (PR-1527)





# PARTS LIST

D	MAIN CHASSIS		1219	25W1'	470 1
	21	IOD: IN 1002	T	TRANSFORMER	
		,	1201	INPLIE	= 1300 %
C	CAPACITOR			OUTFUT	# 320026
	CERAMIC DISC		101	(70)1101	** '',' (M). ()
1 3	50WV	0.047.46	1	INDUCTOR	
Economica communica	(7) 7 V V	0.04771		RE CHOKE	# 000024
RL	RELAY		1201	RE CHOKE	# 220034 # 220011
	AP3241	HC: EVC:195		1204 RF CHOKE	
1	111 0241	110 1 170 120	1205.	1204 NE CHOKE.	# 220035
RLS	RELAY SOCRET A1'384455	HC4 SS			
S	SWITCH				
1		WD-9216		COUPLER UNI	Т
• )	DELAY	WD-9216	PB	PRINTED CIRCUIT BO	DARD
3	BAND 2 2 60	=003505 =003506)		A~Z)	
1		22 08			
Brown telleronomy			D	DIODE	
J	RECEPTACLE			105 Get GB)	1S1007 - 1N270
1	ANT JSO 2	39			
2	INPUT JSO 2	39	R	RESISTOR	
3	POWER QMS	AB6M		CARBON FILM	
			102	J <sub>4</sub> W	82 \
		*	103.1	04	470 Ω
	Bith My New American State of State of committee of commi			1, 11.	10K ©
			-		
			VR	POTENTIOMETER	
	BOOSTER UNIT			EVL VOAA 00B54	50 K O F
PB	PRINTED CIRCUIT BOAR	D			
14441)			C	CAPACITOR	
				DIPPED MICA	
0	TRANSISTOR		101 1	02 50W V	180PF
			101,1	76 00 17 1	\$ 17 LP \$ 3
1203	202 SRF1427 2SD313E(2S	[]235]	† <del></del>	CERAMIC DISC	
A 60 CF EP	64 - 7 3 - 7 4 - 7 1 5 4 5 7 5 7 6 6 5 7	L / fed CJ CJ /		108 50WV	0.01/4
D	DIODE		1017		A 0 2 7 4 8
1201 1	1202 Si	10010	TC	TRIMMER CAPACITO	R
***************************************			101	ECV 1Z.W 10 - 40	
R	RESISTOR				
	CARBON COMPOSITI	ON	T	TRANSFORMER	
	$_{1}$ $=$ $M_{\odot}$			CM COUPLER	# 220027
1203,1	1205 E W	15:2			
1209	$^{-1}$ $\sim$ W				
			:		
	METALIC FILM				
1204,1	1209 1W	39 Ω			
1208	3 W	15 Q	100	CONTROL UN	IT
1202	3W	56 Ω	PB	PRINTED CIRCUIT BO	
1211	3 W	68 Ω		$\Lambda - Z$	An plan and the of Completes (AM)
1201	5W	33 ℃	20021		
1210	6W	24 🖸	Q	IC. TRANSISTOR & 1	THYRISTOR
1610	O VV	99.5	204	10. TRANSISTOR &	"PC 2710
VR	POTENTIOMETER		201	Tr	2SC 372
1201	V18K3-2	5ΚΩΒ	202	A A	2SC 735
1601	VIUIN L	J1 52 1)	203	Thyristor	
С	CAPACITOR		1	r ny r istor	777 311
	DIPPED MICA		D	DIODE	
	500WV	82PF	203,2		1S1007(1N270
1201	500W V	430PF	201,2		10D1(1N4002
1209	500 W V	750PF		21	The same and the s
A Market of the control of the contr	1205,1207,1208 500WV	1000PF	R	RESISTOR	
1204,1	1200, 1201, 1200 300 W V	YOUT I.		CARBON FILM	
-	CERAMIC DISC		209	LANDON FILM	390 9
1210 1	1213, 1220 50WV	0.1/F	205	1 4 M.	680 5
	1610, 1660 OUVV V	0.1,7F	208	1 4 W	1Ks
1610,1			1		27 K s
16010, 1	ELECTRON VITA		71345		
	ELECTROLYTIC		206	1 W	
1211	ELECTROLYTIC 16W V 25W V	330 / F 10 / ℓ F	206	1 W	33K 9 390K 0



203,204	MW	nooko	L INDUCTOR
/n 4 m m	ON COMPA	T ISTERNAL	301,320 160m LOWPASS # 220148A
207	ON COMPO:	STERON 22 O	303,304 80m LOWPASS # 220147A
407	77.74	Zi U	305,306 40m LOWPASS # 220214
ALL POSTERIA	Long & B prompt prompts		307 20m LOWPASS(A) # 220254
	IOMETER	AND PARTY OF THE P	208 20m LOWPASS(B) #220215A
202,203 E		00B54 50K 2B	309 15m LOWPASS(A) # 220216
201 E	VL VOAA	00B26 2MΩB	310 15m LOWPASS(B) #220217
C CAPACIT	TOP		311,312 10m LOWPASS #220218
	MIC DISC		
202-207,209,21		0,01pF	
NOT A CAR	ALUM		
208	16WV	0.22/41/	LED BOARD
201	16W V	1,017	PB PRINTED CIRCUIT BOARD
471	1211	1,72	1578A RECOPER INDICATOR
RL RELAY			1579 AFP INDICATOR
201	G2E.		1008 OLI BRAGACTA
277	7.00		D LED
			401 SG 103D
			402,501 SR 103D
	- The state of the	the later was the second secon	
			R RESISTOR
*	LPF UNIT		CARBON FILM
PB PRINTE	D GIRCUIT E	SOARD	401 MW 390 t
157711			
D DIODE			
301 - 305	GetGBT	151007(1N270)	
	and the contract of the contra	nendomicamon de suno aquesta como concordo esta estrutor a sociolo en informecio esta como de	
R RESISTI	OR		ACCESSORIES
CARI	MON FILM		COAXIAL PLUG JPL 259 2
362	14 W	82 ()	DC POWER CORD # 240026
303,304	⅓ W	47011	POWER PLUG QMS-6FK (I)
301	HW	Lako	FUSE HOLDER SN-1102 (1)
			FUSE 30A 113
	TOMETER		FUSE :IOA I
301 E	VL-VOAA	001154 SOK 1213	
G CAPACI	TOR		
	ED MICA		
301,302	50WV	180PF	
325	500WV	82F°F	Authorities Sales After the Authorities and Au
327	500WV	100PF	
324	BROW V	110PF(56PF×2)	
322	500W V	120PF	
326	500WV	130PF(68PF×2)	
323	500W V	150PF	
321	500 W V	170PF(82PF×2)	
319	500W V	270 PF	
318,320	500W V	300 PF	
316	500 W V	3901°F	
317	500WV	680PF(308PF×2)	
315	500 W V	626PF	
313	500 W V	0.80 F.F.	
310,312,314	500WV	1200 PF	
311	509W V	2000 PF	
£*3211	AMIC DISC		
303~308	SOW V	0.01eF	
		N. W. S. S.	
ELE	CTROLYTIC		
328,329	16W V	1/42	
d			
	ER CAPACIT		
301 1	SCV 1ZW 1	0×32 10PF	
T TRANSI	FORMER		
	M COUPLI	ER #220027	
301			

